



WF-8900 Power Centers

Item	Specifications				
Model Number	WF-8935	WF-8945	WF-8955	WF-8965	WF-8975
Power Consumption	600 W	780 W	950 W	1260 W	1300 W
Input Voltage	105 VAC-130 VAC, 60 Hz				
Output Current	35 A	45 A	55 A	65 A	75 A
Converter Type	Three-Stage Converter/Charger				
Voltage Output	13.2-14.4 Vdc range				
Absorption Mode	13.6 Vdc range (nominal voltage)				
Bulk Mode	14.4 Vdc range (quick charging voltage)				
Float Mode	13.2 Vdc range (trickle charge voltage)				

Safety Features/Protections					
Over Current	Yes	Yes	Yes	Yes	Yes
Over Temperature	Yes	Yes	Yes	Yes	Yes
Over Voltage	Yes	Yes	Yes	Yes	Yes
Reverse Polarity	Yes	Yes	Yes	Yes	Yes
Short Circuit	Yes	Yes	Yes	Yes	Yes
Cooling Fan	Yes	Yes	Yes	Yes	Yes

Shipping					
Outside Dimensions	13.875" (W) x 11.625" (H) x 9" (D)				
Weight	7.0 lbs.	7.75 lbs.	7.0 lbs.	9.75 lbs.	10.0 lbs.

Installation (applies to all models)

AC Circuits	6 ("Main" and 5 branch circuits)
DC Circuits	11 (9 20A max) (2 30A max)
Case Material	Plastic (brown and black)



Standards (applies to all models)

Comply with FCC	Yes	WF-8955/65/75 New Generation	WF-8935/45	WF-89xxANP/T30 30A Transfer Switch (option)	WF-89xxMBA (Converter replacement)
------------------------	-----	---------------------------------	------------	---------------------------------------------------	---------------------------------------

Specifications are subject to change without notice or obligation.

www.wfcoelectronics.com